

Project :	Date :
Cat No. :	Type :
Notes :	Volts :

Aluminum recessed downlights can provide lights where it's needed; cabinets, ceiling, walls, stair and many more applications.

Designed with Cree LED can be used in 1W 350MA for enclosed applications or in cabinets and in 3W 700MA for open installations.

### RECESSED LED 1W-3W (350-700MA)


<b>Cri:</b>	<80	
<b>Light color:</b>	5000K white	140lm
	3000K warm white	120lm
<b>Fixture finish</b>	Anodized Aluminum	
<b>Fixture material:</b>	Aluminum	
<b>Optic:</b>	NTL-010	120°
	NTL-020-30-50	45°
<b>Voltage:</b>	1W 350MA / 3W 700MA	
<b>Lamp life:</b>	>50,000 hours CREE	
<b>Maximum wattage:</b>	3 WATTS	
<b>Fixation:</b>	Spring clip except NTL-050 snap clips	
<b>Working temperature:</b>	-40 - +50°C	
<b>Certification:</b>	Conform to ANSI/UL standard 2108, Certified CAN/CSA standard 22.2-9.0	

**Driver constant current Class II and for dimming option consult factory**


\* Available 12VDC non dimmable




NTL-010-RD-3W-XX-MA




NTL-020-RD-3W-XX-MA



NTL-030-RD-3W-XX-MA



NTL-050-RD-3W-XX-MA



### Ordering Matrix / Specification

Model	Wattage	Color	Voltage
	3W		
NTL-010-RD-	50	White	350MA 1W
NTL-020-RD-	30	Warm white	700MA 3W
NTL-030-RD-			
NTL-050-RD-			



Project :

Date :

Cat No. :

Type :

Notes :

Volts :

**CONSTANT CURRENT  
FOR USE 1 WATT (350MA)**

**CONSTANT CURRENT  
FOR USE 3 WATTS (700MA)**

NTLD3W-350MA-12	CAN DRIVE
Input voltage 12VDC	1 TO 3



NTLD9W-700MA-12	CAN DRIVE
Input voltage 12 VDC	1 TO 3

Dimmable when used with NTM-XXL-12VDC

NTLD350MA	CAN DRIVE
Input voltage 120VAC non dimmable	1 TO 6



NTLD700MA	CAN DRIVE
Input voltage 120VAC non dimmable	1 TO 3

NTLD350MA-WP	CAN DRIVE
Input voltage 120VAC non dimmable	1 TO 6



NTLD700MA-WP	CAN DRIVE
Input voltage 120VAC non dimmable	1 TO 3

NTLD3548	CAN DRIVE
Input voltage 0-120VAC dimmable	8 TO 14



NTLD7036	CAN DRIVE
Input voltage 0-120VAC dimmable	6 TO 10

\*must use recommended dimmer

\*must use recommended dimmer

**DIMMABLE / REMOTE OR MANUAL**

NLT3200-350	CAN DRIVE
If input is 12VDC	1 TO 3
If input is 24VDC	1 TO 7
If input is 36VDC	1 TO 10



**DIMMABLE / REMOTE OR MANUAL**

NLT3200-700	CAN DRIVE
If input is 12VDC	1 TO 3
If input is 24VDC	1 TO 7
If input is 36VDC	1 TO 10

**dimmable DMX 3 ZONES**

NTDMX512-3C-350MA	CAN DRIVE
If input is 12V	1 to 3 per zone
If input is 24V	1 to 6 per zone
If input is 36V	1 to 10 per zone
If input is 48V	1 to 12 per zone



**dimmable DMX 3 ZONES**

NTDMX512-3C-700MA	CAN DRIVE
If input is 12V	1 to 3 per zone
If input is 24V	1 to 6 per zone
If input is 36V	1 to 10 per zone
If input is 48V	1 to 12 per zone